

size 60×60

05_23.12.07

SMARTCOBY Pro SLIM

35W2C1A

取扱説明書

1.はじめに

35W出力対応モバイルバッテリー

ご購入ありがとうございます。ご使用前に「取扱説明書」をよくお読みの上、正しくお使いください。

もくじ

1.はじめに

2

2.注意事項

3-5

3.付属品

6

4.仕様

6

5.対応急速充電規格

6

6.各部名称

7

7.使用方法

8-11

8.製品保証

12-13

2.注意事項

警告

死亡や重傷に結びつく恐れがある内容です。

注意

充電を行う可能性及び、物理的損傷に結びつく恐れがある内容です。

警告

本製品が異常な発熱、異臭、異物が入った場合は直ちに使用を中止してください。

注意

分解及び改造は絶対に行わないでください。火災・感電・怪我の原因となります。

注意

お子様だけで使用、幼児の手の届くところを使用しないでください。

注意

本製品にスマートフォンやPCを接続した際に充電・放電の速度が低下する場合があります。

注意

高温となる場所での使用、設置、保管は避けてください。また火の中へ投入しないでください。

注意

本製品を落としたり、重いものを上にのせてください。衝撃をあてないでください。感電・感熱・怪我の原因となります。

注意

本製品は熱を発する装置から離れて使用してください。

3.付属品

■本製品

充電ケーブル(USB-C to USB-C) 充電ケーブル

型番: CIO-MB35W2C1A-10000-S

バッテリー容量: 10000mAh

入力(USB-C1/C2): 5V=3A/9V=3A/12V=2.32A/15V=2.33A/20V=1.75A (MAX 35W)

出力(USB-C1/C2): 5V=3A/9V=3A/12V=2.32A/15V=2.33A/20V=1.75A (MAX 35W) PPS:3.3-11V=3A(MAX 33W)

出力(USB-A): 4.5V=5A/5V=3A/9V=2.5A/12V=1.5A (MAX 22.5W)

USB-C1+C2: 合計30W

USB-C1+A or C2+A: 合計30W

製品サイズ: 約97.6×69×16.2mm

重量: 約180g

サイクル回数: 約500回

充電時間: 約90分

■5.対応急速充電規格

PPS / PD3.0 / QC4.0+

6.各部名称

①バッテリー残量数値LED

(%表示・充電マーク)

②USB-C1ポート(入出力)

③USB-C2ポート(入出力)

④USB-Aポート(出力のみ)

⑤バッテリー残量確認ボタン

(電源オフ:1回押す)

(電源オン:2回押す)

バッテリー残量LED

充電中

充電完了

モバイルバッテリー使用中

7.使用方法

■デバイスへの充電方法

USB Type-Cケーブルを使用して、本製品とデバイスを接続し充電を行います。自動的に充電が始まらない場合は、本製品の側面にある「バッテリー残量確認ボタン」を押してください。

デバイス充電が開始されるとデジタル残量が「%」表示になります。

※急速充電(Power Delivery)を行うためには、急速充電に対応したデバイスと、急速充電に対応した充電ケーブルが必要となります。

■バッテリー残量の確認方法

本製品に何も接続されていない状態で、本製品の側面にある「バッテリー残量確認ボタン」を押すことで、バッテリー残量(0-100%表示)が表示されます。もしも本製品とデバイスと接続し、デバイスへ充電が開始されてもバッテリー残量(0-100%表示)が表示されます。

8.製品保証

■複数同時充電方法

USB Type-C1・C2・USB Type-Aの各ポートを使用して、本製品とデバイスを接続し充電を行います。最大4台の同時充電が可能です。自動的に充電が始まらない場合は、本製品の側面にある「バッテリー残量確認ボタン」を押してください。

2台同時充電(例)

3台同時充電(例)

※複数同時充電時は本製品が熱くなる場合がございますが、本製品及びデバイスが満充電に近づくにつれ通常の温度に戻ります。

■本製品への蓄電方法

USB-Cケーブルを使用して、本製品のUSB-C1及びC2ポートにUSB充電器などを接続することで本製品の蓄電が開始されます。

2台同時充電(例)

※最大35Wの蓄電を行うためには、35W出力に対応したUSB充電器が必要となります。USB充電器はCIO製品を推奨します。

※複数ポートでの同時蓄電には対応しておりません。

■バススルー充電方法

USB-C1及びC2のどちらかに充電器と充電ケーブルを接続し、ケーブルの接続しない方のUSB-C1・USB-Aポートにデバイスを接続することで、デバイスを充電しながら本製品に蓄電が開始されます。

バススルー充電(例)

※デバイス側が優先して充電されます。

※バススルー時は本製品が熱くなる場合がございますが、本製品及びデバイスが満充電に近づくにつれ通常の温度に戻ります。

※バススルー充電時、USB-AにApple Watchなどの低電流端末を接続すると、充電ができません。予めご了承ください。

8.製品保証

この度は株式会社CIOの製品をご購入いただき誠にありがとうございます。商品に初期不良などの不具合がある場合、レビューの前にご連絡ください。自動的に充電が始まらない場合は、本製品の側面にある「バッテリー残量確認ボタン」を押してください。

正しくご使用いただいた状態で保証期間内に発生した故障の場合も、交換対応を実施させていただきます。

納品書兼保証書もしくは、販売店シートが保証書の代わりとなりますので大切に保管してください。

※商品の保証は原則、交換対応とさせていただきます。

返品・返金は承っておりませんのでご了承ください。

以下の場合保証を實施いたしかねますので、ご了承ください。

1. 使用上の取り扱い不注意による事故(落下や水没など)。

2. 使用者による任意での内部改造による故障。

3. 火災・水害などによる故障。

8.製品保証

■製品お問い合わせ窓口

<https://connectinternationalone.co.jp/contact/customer/>

QRお問い合わせフォーム または下記メールアドレスよりお問い合わせください。

メールアドレス: customer@connectinternationalone.co.jp

保証書【CIO-MB35W2C1A-10000-S】

販売店名

保証期間: 1年

お買い上げ年月日: 年 月 日

CIO 公式 LINE アカウント

フォローしてね!

メッセージ01 LINEでカスタマーサポート

故障時や使い方が分からない場合など、チャットからスムーズにLINEで簡単なお問合せOK! 是非お気軽にご利用ください。

メッセージ02 LINE限定クーポン

Amazonや楽天市場などでご利用いただける最新お得なクーポンをLINEでいち早く公開! SALEや新商品の情報も盛りだくさんです!

COUPON & SALE

お得意なクーポン

セール情報

QRコードでLINEの友達を追加

QRコードをスマートフォンでスキャンしてください。

CIO 公式 YouTube アカウント

チャンネル登録してね!

メッセージ01 市場未公開情報ゲット!

開発中の商品情報や開発秘話などをもっと早く公開! 市場未公開の商品情報もCIO社員が詳しく解説します!

メッセージ02 欲しい商品が見つかる!

新しくスマホやPCを買ったけどどんな充電器、製品が最適なんだろう... CIOの製品の特長を分かりやすく解説! あなたに合うデバイスが見つかる!

QRコードでYouTubeのチャンネル登録

QRコードをスマートフォンでスキャンしてください。

05_23.12.07

SMARTCOBY Pro SLIM

35W2C1A

USER MANUAL

1. Introduction

Thank you for your purchase. Please read the "USER MANUAL" carefully before use and use it correctly.

Contents

1. Introduction

3

2. Precautions

4-6

3. Accessories

7

4. Specifications

7

5. Supported Fast Charging Protocols

7

6. Names of Each Part

8

7. How to Use

9-12

8. Warranty

13-14

2.Precautions

Warning

This is content that could lead to death or serious injury.

Caution

There is a possibility of serious injury or damage to property.

Warning

Stop using this product immediately if it makes any noise, generates unusual heat, has an unusual odor, or contains a foreign object. Do not disassemble or modify this product in any way. It may cause a fire, electric shock or injury.

Caution

Children should not use this product alone. Do not use this product within the reach of children.

Caution

Do not immerse the product in water or allow it to get wet. Do not touch the power plug with a wet hand. Otherwise, it may cause heat generation, fire, fire, electric shock, or explosion.

Caution

Please do not use, leave or store the product in a high temperature environment. Do not throw this product into fire.

Caution

Do not drop this product, place heavy objects on it, or give it a strong shock. Failure to do so may result in electric shock, malfunctions or injuries.

Caution

When charging with Power Delivery (PD), it is necessary to use a PD compatible device and a PD compatible cable.

Caution

Plug the power cord into a household wall outlet when using. Failure to do so may result in fire or electric shock.

Caution

This product should be used away from heat-generating equipment.

3. Accessories

■SMARTCOBY 35W2C1A ■Charging Cable(USB-C to USB-C) ■User's Manual

Model: CIO-MB35W2C1A-10000-S

Battery Capacity: 10000mAh

Input (USB-C1/C2): 5V=3A/9V=3A/12V=2.32A/15V=2.33A/20V=1.75A (MAX 35W) PPS:3.3-11V=3A(MAX 33W)

Output (USB-C1/C2): 5V=3A/9V=3A/12V=2.32A/15V=2.33A/20V=1.75A (MAX 35W) PPS:3.3-11V=3A(MAX 33W)

Output (USB-A): 4.5V=5A/5V=3A/9V=2.5A/12V=1.5A (MAX 22.5W)

USB-C1+C2: Total 30W

USB-C1+A or C2+A: Total 30W

Size: Approx. 97.6×69×16.2mm

Weight: Approx. 180g

Lifecycle: Approx. 500times

Time to Recharge: Approx. 90minutes

4. Specifications

Size: Approx. 97.6×69×16.2mm

Weight: Approx. 180g

Lifecycle: Approx. 500times

Time to Recharge: Approx. 90minutes

5. Supported Fast Charging Protocols

PPS / PD3.0 / QC4.0+

6. Names of Each Part

①Remaining Battery Indicator

in % and Charging Animation

②USB-C1 (Input / Output)

③USB-C2 (Input / Output)

④USB-A (Output)

⑤Battery Level Check Button

Press it Once to Power ON

Press it Twice to Power OFF

Remaining Power LED

Power Bank in Use

Charging in Progress

7. How to Use

■ How to Charge the Device

Use the USB-C cable to connect the product to the device for charging. If charging does not start automatically, press the button on the side of the product.

When charging to the device starts, the digital remaining charge will show in %.

* In order to use fast charging (Power Delivery), a device that supports fast charging and a charging cable that supports fast charging are required.

■ How to check the remaining battery

Press the button on the side of the product when nothing is connected to the product, and the remaining battery level (0-100%) will be indicated on the display. Alternatively, the remaining battery level (0-100%) will be displayed when the product is connected to a charging device.

■ Multiple Devices Simultaneous Charging

USB-C1, C2, and USB Type-A ports are used to connect and charge the product and devices. Up to three devices can be charged simultaneously. If charging does not start automatically, press the button on the side of the product.

2 units simultaneous charging (Example)

3 units simultaneous charging (Example)

* The product may become hot when charging multiple devices at the same time, but the temperature will return to normal as the product and devices get to full charge.

■ How to Recharge the Device

Using a USB-C cable, connect a USB charger or other device to the USB-C1 port of this product to start charging this product. * USB-C2 port does not support input.

* A USB charger that supports 35W output is required to charge up to 35W. CIO charger is recommended. * Simultaneous recharge to the battery through multiple ports is not supported.

* Devices are charged first.

* The product may become hot when charging multiple devices at the same time, but the temperature will return to normal as the product and devices get to full charge.

* Please be aware that during pass-through charging, connecting low-current devices such as the Apple Watch to the USB-A port will not enable charging.

■ How to Charge by Using Pass Through

When a charger and charging cable are connected to the USB-C1 port and a device is connected to the USB-C2 or USB-A port, the product will be charged while charging the device.

Pass-through Charging (Example)

* Please note that we do not accept returns or refunds.

Please note that the warranty cannot be provided in the following cases.

1. Accident due to careless handling while using it. (e.g. dropping, submerging and so on.)

2. Failure due to any internal modification by the user.

3. Failure due to fire or water damage.

8.Warranty

Thank you for purchasing CIO product. If the product has any defects such as initial malfunction, please contact us before reviewing. We will replace it as an initial malfunction product. In case of malfunction occurred within the warranty period or correct use, we will also replace it.

Invoice/warranty or dealer's receipt will become warranty so please keep it. The product will be guaranteed for replacement with it.

Please note that we do not accept returns or refunds.

Please note that the warranty cannot be provided in the following cases.

1. Accident due to careless handling while using it. (e.g. dropping, submerging and so on.)

2. Failure due to any internal modification by the user.

3. Failure due to fire or water damage.

8.Warranty

Support Information

Email address: smartcoby@connectinternationalone.co.jp

One Year Warranty【CIO-MB35W2C1A-10000-S】

Dealer's Name

The date of purchase:

CIO Co., Ltd.

Stay Updated with All the Latest News!

We will be posting information about our new crowdfunding project, new products, and special discounts.