







★警告 死亡や重傷に結びつく恐れがある内容です。 ★ 注意 重傷を負う可能性及び、物的損害に結びつく恐れがある内容です。

★製品で異音や異常な発熱、異臭、膨張、または異物の侵入が確認された場 分、すぐに使用を中止してください。 ◆ 分解及び改造は絶対に行わないでください。火災・感電・怪我の原因となりま

○ 高温となる場所での使用、放置、保管は避けてください。また火の中へ投入し

へ 本製品を落としたり、重いものを上にのせたり、衝撃をあたえないでください。 ○ 感電・故障・怪我・発煙・発火の原因となります。 電源プラグは、家庭用コンセントに奥までしっかりと差し込みご使用ください。

本製品は熱を発する装置から離して使用してください。 スタンドの取り扱いには注意してください。破損・故障・怪我の原因となります。

○ 発熱、発火の原因となります。

2.注意事項

どさい。またデバイス機器側が満充電、又は製品本体が満蓄電に近づくにつれ、通常の温

Power Delivery(PD)充電を行う際は、PD対応デバイス機器に対応したPD対応ケーブ
ルをご使用いただく必要がございます。

本製品を水につけたり、漂らさないようにしてください。発熱・発火・火災・感 雷・破裂などの原円とかわます。

をし込みが不十分だと、接触不良などによって火災や感電の原因となります。 周囲の温度が高い場合、ワイヤレス充電器は発熱を抑えるために出力を自動的に制限

ネットワイヤレス充電機能を使用するときは本製品が熱くなる場合がありますが、 ● 本製品は磁石が内蔵されています。クレジットカードなどを本製品に近づけたり挟まれいようにしてください。磁気やRFIDチップの破損につながる可能性があります。

品を引火性のある油、化学薬品、可燃性のものの近くで使用しないでください。

■ 本製品を使用して接続された機器の破損・損傷・故障およびデータの消失に関して弊社
では一切の責任を負いかねます。あらかじめご了承ください。

は改善のため予告なく変更する場合があります。そのため説明書記載の

装着したままご使用にならないでください。異物検知機能が働き正しく充電できません。

長時間使用しない場合は、製品寿命を保つため約3か月に1度の頻度にて充電・放 1 電左に、アイメさい。

ISB-C+マグネットワイヤレス / Apple Watch 5V=3A 15W Max 製品サイズ:約93.0×63.0×15.6mm リング部:+2.15mm 重量:約140g サイクル回数:約300回 蓄電時間:約115分

の社名、製品名などは各社の商標、商標登録です。 一定の温度になると充電が停止するため、しばらく冷やしてから再度使用してください。 こもりやすい環境(布団やバッグ内など)で使用しないでください。



CIOのパッテリー回収サービスのご利用をお勧めします。

(https://connectinternationalone.co.jp/ciopbcollect/)

 ⚠ Caution

Power Delivery (PD) charging, it is necessary to use a PD-compatible cable for

not work or charging may become slow. In this case, please ver. Also, please note that wireless charging cannot be done

When using the magnetic wireless charging function, please make sure that
the device is compatible with wireless charging before using it.

not use this product for any purpose other than its intended use.

Do not use or store the product in a place where it is exposed to water or other liquids.

Please note that the product may become hot during charging at high power, so please handle it with care. It will return to normal temperature as the device and the product are fully observed.

nd the product are fully charged.

JSB-C PD出力:5V=3A / 9V=2.22A / 12V=1.67A(Max 20W)

> ※対応iPhoneシリーズは最大7.5Wとなります。 皮膚や衣服に付着した場合には、直ちに水道水などのきれいな水で洗い流してくだ
>
> さい。目に入ったたきは、こすらずに直ぐに水道水などのきれいな水で洗った後、直
> ちに展開の治療を受けてんださい。
>
> IISR-Cエグイネットワイヤレス / Apple

デバイスの存電時間はメーカー公称値と異なる場合があります。



■SMARTCOBY Ex02 Wireless Charger (Magnet & Watch) plus Stand

SMARTCOBY Ex02 Wireless Charger (Magnet & Watch) plus Stand

■User Manual ■Charging Cable (USB-C to USB-C) 50cm

USB-C PD Input:5V=3A / 9V=2A / 12V ==1.5A(Max 18W)

The maximum supported iPhone series is 7.5W.

USB-C+Magnet Wireless / Apple Watch 5V = 3A 15W Max

Size :Approx. 93.0×63.0×15.6mm ring+2.15mm

Guaranteed operation temperature: 0°C-35°C

Product material: ABS+PC(WH) Product material: PC(BK)

Qi charging/Fast Magnetic Wireless Charging

Battery storage time: Approx, 115 minutes

USB-C PD Output:5V=3A / 9V=2,22A / 12V=1,67A(Max 20W)

Model:CIO-MB20W1C-5000-EX02

Capacity: 5000mAh 3.7V 18.5Wh

Magnet Wireless: 5W/7,5W/10W/15W

PPS: 3,3-11V = 2A(Max 22W)

Apple Watch: 2.5W Max


Weight: Approx. 140g

PD3,0 QC4,0+ PPS

■有線充電優先切り替え(急速充電モード)の方法

・トへ近づけ磁気吸着させます。

②スタンド



・ でも、一クルをナバイスに接続しても、自動的ない場合は、「電源ボタン」を押してください。

※Power Delivery(PD)充電に対応した20W以上の充電アダ プターを推奨。20W未満の充電アダプターでも充電は可能です が、充電速度は遅くなる場合があります。 ※対応する充電アダプターをお持ちでない場合はCIOが販売する 充電アダプターがおすすめです。

6.Names of Each Part

© LED remaining capacity display

How to switch to wired charging priority (fast charging mode)

4 3 4

① Apple Watch &

Magnetic Wireless Charging Area

Power off Double click the power button)

?. MagSafe対応デバイスへのワイヤレス充電の場合



ワイヤレス充電ポイント

吸着するとワイヤレス充電が開始されます。Qi対応スマートフォンもワイヤレス た電に対応していますが、磁力による吸着機能はMagSafeやQi2対応デバイスに 限定されます。充電中、緑色の稲妻マークが点灯します。

《必ず、接続されたデバイスが本製品から落下しないことを確認してからご使用ください 固定が不安定な状態で使用すると、落下による破損の恐れがあります。 フイヤレス充電中は、製品本体およびデバイスが熱を帯びる場合がありますが、 てれは通常の仕様です。

7.How to Use

Use the USB-C cable to connect this product to your device

ing adapter less than 20W, but the charging speed may

s slower.

you do not have a compatible charging adapter, we commend the charging adapter sold by CIO.

If charging does not start automatically, press the power button to start,

■ 7-1.How to Charge Devices

Charge via Cable

for charging.

3. ワイヤレス充電



MagSafe充電対応AirPodsの場合、上図のように製品本体に吸着 するとワイヤレス充電が開始されます。 ※ワイヤレス充電は製品本体とデバイスの位置がずれると正しく充電されませんので

Wireless Charging for MagSafe Compatible Devices

MagSafe-compatible or Qi2-compatible devices, e adsorbed, wireless charging will start. Qi-enabled smartphones also

f you remove the device from this product during wireless charging and stop charging, the wireless charging To restart, press the power button or furn off the power and then turn it on again. Please use it.

*Be sure to check that the connected device will not fall from this product before use. If it is used with unstable fixation, there is a risk of damage due to falling.

*During wireless charging, the product and device may become hot. This is a normal specification.

Wireless charging

Wireless charging point

※すべてのワイヤレス機器での動作を保証するものではありません ※充電時間はデバイスの性能、バッテリー残量により異ます。

Apple Watchの「設定」をタップ>「パッテリー」をタップ>「パッテリーの状態」をタップ>「パッテリー充電の最適化」のチェックを外します。 ●Apple Watchの仕様上、充電が一時的に止まる事がございますが、自動的に 面間します。

pple Watchを製品本体のワイヤレス充電エリアに置くと(磁気吸着)、

充電が開始されます。その際、緑色の稲妻マークが点灯します。



ヤレス充電エリアに吸着・置くことでワイヤレス充電がはじまりま

がはじまります。 2台同時充電は高出力となるため、本製品が熱くなる場合がありますが異

イヤレス充電は最大15W、有線充電は最大20W。合計15W出力となり 2台同時に充電する場合、緑色の稲妻マークは消灯します。 ※2台同時に充電すると、各デバイスへの出力が低くなるため、充電に時間が

② 本製品とケーブル充電対応デバイスを充電ケーブルで接続し充電

※接続するデバイスにより、充電速度や時間は異なります。

When you place your Apple Watch in the wireless charging area

u use it in an unstable place, Apple Watch may fall. Please use it

'ery Charge Optimization' needs to be deactivated to allow charging

o "Settings" on your Apple Watch > tap "Battery" > tap "Battery Health" uncheck "Optimized Battery Charging".

This product is not Made for Apple Watch. Please note that these figures

Due to the specifications of the Apple Watch, charging may stop temporarily, but will resume automatically.

the product itself (magnetic adsorption), charging will begin. At t time, the green lightning mark will light up.

The maximum power output to the Apple Watch is 2.5V

When using wireless charging, the product and device m hot, but this is not a malfunction. This will return to normal t as the device gets closer to full charge.

to disable battery charging optimization]

【マグネットワイヤレス充電および ワイヤレス充電について】 ●ワイヤレス充電を使用すると、本製品及びデバイスが熱くなることがありますが異常では

【バッテリー充電の最適化の解除方法】

6. Pass-Through Function

ありません。デバイス側が満充電に近づくにつれ通常の温度に戻ります。

●iPhoneはバッテリー保護のため約80%付近から充電速度がゆっくりとなります。 ●iPhoneのパッテリーの劣化を軽減するために約80%付近で一時的に止まる「バッラ リー充電の最適化」という機能があります。解除することで80%を超える充電が可能と

iPhoneの「設定」をタップ>「バッテリー」をタップ>「バッテリーの状態」をタップ> 「パッテリー充電の最適化」のチェックを外します。 ●本製品に付属の充電ケーブルは急速充電(Power Delivery)に対応しています。 ●3mm以上の厚みのある保護ケースや、カバーではワイヤレス充電できない場合があり ます。MagSafeの場合も充電中に本製品とデバイスがずれたり厚みの問題で充電出

来ない場合があります。ケースを外すかMagSafe対応の純正ケースを装着する事を推 ●ワイヤレス充電は本製品とデバイスの位置がずれると正しく充電されませんのでご注意 ●充電器は別売りです。別途ご準備ください。

●金属等の装飾があるスマートフォンケースなどを装着している場合、異物検知機能が動 作しワイヤレス充電ができません。 ●異物検知機能(FOD)が作動すると、無線出力および有線出力が一時的に停止します 場合のみ、有線出力が再開されます。異物が取り除かれた後、デバイスを再度吸着させ

●保護ケースをお使いの場合は必ずMagSafe対応のケースをお使いください。 ●ワイヤレス充電は、動作保証温度内にてご利用ください。動作保証温度外で使用すると 充電効率が悪くなり、出力が低下することがあります。

. Connect the product and charger using the charging cable.

2. Pass-through charging will begin when you attach and place

●The device will be charged first, and when the device is fully charged, the product will begin to be charged.

charging area of the product as shown in the image above.

The charger is sold separately. A 18W or higher charger is recommended

The green lightning bolt symbol will turn off during pass-through charging

Pass-through charging takes longer than regular charging

Charging speed and time may vary depending on the connected device.

■ 7-2.製品本体への蓄電

この度は株式会社CIOの製品をご購入いただき誠にありがとうございます。 テリー残量表示LEDが点滅し、「100」と表示されれば著

★ USB Type-C 入力 元電器

2. 使用者による任意での内部改造による故障。

7-2.How to Recharge

7-3.stand Function

from falling or as a stand.

Connect to the charging adapter using the included

USB-C cable. After connecting to this product, the

displayed, power storage is cxmplete. USB-C Input

₩all Charger 🗐 👝

•In order to perform quick charging (Power Delivery), you will need a charge that supports quick charging and a charging cable that supports quick

The charging cable included with this product supports quick charging

●In order to perform rapid power storage of up to 18W, a power adapter that

When considering long-term battery life, it is best to maintain the battery

The charger is sold separately. Please prepare separately.

The stand rotates 360° and can be erected up to

approximately 90° Can be used to prevent devices

Do not force the stand open or apply excessive force. Doing so may cause damage, malfunction, or injury.

3.Please be careful not to let foreign objects get between the stand and the storage space.

remaining battery power indicator LED on the side

with the USB-C port will blink, and if "100" is

■ 7-3.スタンド機能 スタンドは360°回転し、約90°まで立てることができます。

Magnetic Wireless Charging and Wireless Charging

reduce the degradation of the battery, the iPhone may temporarily stop charging at around 80%. You may be able to charge your iPhone

Tap "Settings" on your iPhone > tap "Battery" > tap "Battery Health" > uncheck "Optimized Battery Charging".

•When using wireless charging, this product and the device may

•The iPhone's 'Battery Charge Optimization' function slows down the

beyond 80% by deactivating "Battery Charge Optimization"

Wireless charging may not work with protective cases or coverage thicker than 3mm. In the case of MagSafe, charging can done due to the thickness of the case or the device sliding to the case or the ca

Please note that wireless charging will not work properly if the product and the device are not in the correct position.

olf your smartphone is wearing a case with metal or other decoration,

•When using a protective case, be sure to use a MagSafe compatible

ne foreign object detection feature will be activated and wireless

normal as the device gets closer to full charge.

How to disable battery charging optimization]

use a genuine MagSafe compatible case

reduce charging efficiency and power output.

デバイスの落下防止やスタンドとしてご利用いただけます。

タンドは安定した位置でご使用ください。 スタンドを無理に開いたり、過度な力を加えない でください。破損や故障、怪我の原因となる恐れ 3.スタンドと収納スペースの間に異物が入らないよ うご注意ください。



正しくで使用いただいた状態で保証期間内に発生した故障の場合も 交換対応を実施させていただきます。

保証書の代わりとなりますので大切に保管してください。

(下の場合は保証を実施いたしかねますので、ご了承ください。 1. 使用上の取り扱い不注意による事故(落下や水没など)。

https://connectinternationalone.co.jp/contact/custome

故障時や使い方が分からない場合など、チャットだからスムーズ! LINEで簡単にお問合せOK! 是非お気軽にご利用ください。

保証書【CIO-MB20W1C-5000-EX02】

hank you for purchasing CIO product. If the product has any defects

uch as initial malfunction, please contact us before reviewing.

use, we will also replace it.

In case of malfunction occurred within the warranty period or correct

nvoice/warranty or dealer'a receipt will become warranty so please

keep it. The product will be guaranteed for replacement with it.

Please note that the warranty cannot be provided in the following cases.

Please note that we do not accept returns or refunds.

(e.g. dropping,submerging and so on.)

Failure due to any internal modification by the user.
 Failure due to fire or water damage.

お買い上げ年月日: 年 月 日





チャンネル登録してね!

メリット 01 市場未公開情報ゲット!

開発中の商品情報や開発秘話などをいち早く公開!

市場未公開の商品情報をCIO社員が詳しく解説します!

メリット02 欲しい商品が見つかる!

新しくスマホやPCを買ったけどどんな充電器、製品が最適なんだろ





USER MANUAL

CIO Co., Ltd.

ing and sales company focused on dealing with the latest gadgets and smartphone accessories. With the concept of "Delivering the latest, most exciting gadgets", the company offers its products

for users. We offer high quality products in accordance with performance as only an overseas manufacturer can.

Founded in 2017 in Osaka, Japan, CIO Co., Ltd. is a manufactur-

We always pay attention to the latest technology and continuously strive to develop products that increase the level of convenience 7-1. How to Charge Devices 9 Japanese standards, but at the same time, we offer high cost 7-1.1. Charge via Cable 9

6. Names of Each Part · · · · · 8

It is our pleasure to provide convenient gadgets to our customers.

through its e-commerce site and physical stores.

Do not disassemble or modify this product in any way. It may cause a fire, electric shock or injury. Children should not use this product alone. Do not use this product within

Please note that we are not responsible for any damage, breakage, breakdown or loss of data on devices connected to this product. Supported Fast Charging Protocols · · · · · 7

Please do not use, leave or store the product in a high temperature environment. Do not throw this product into fite.

7-1.2-3. Wireless Charging 10-11 7-1.4. Charging your Apple Watch 12

7-1.5. Two Device Simultaneous Charging 13 7-1.6. Pass-Through Function · · · · · · · 14 About magnets and regular wireless charging 15

7-3.stand Function · · · · · · 16

8. Warranty------17-18

Please read the user manual carefully before use and use it correctly. Caution There is a possibility of serious injury or damage to property.

Stop using this product immediately if it makes any noise, generates

Note: The stop using the product immediately if it makes any noise, generates and this product may become not while charging or using it.

Please note that this product may become hot while charging or using it.

If we will return to normal temperature in the product approaches full charge, it will return to normal temperature. O unusual heat, has an unusual odor, or contains a foreign object.

O Doing so may result in electric shock, malfunction, injuries, or smoke/fire. This product may become hot when using the magnetic wireless charging Innction, but this is not a problem. If the plug is not inserted properly, poor contact may result in fire o

This product should be used away from devices that generate heat. Be careful when using the kickstand. Failure to do so may result in damage,

◆製品は磁石、電磁波を生じる無線送信機を内蔵しています。これらの部品はペースメーカーなどの医療用機器に干渉する恐れがありますので、ご使用にあたって、医師と相談の上ご使用ください。

プネットワイヤレス充電機能を使用するときは、デバイスへ金属製の保護カバーなどを

● 充電速度が低下することがあります。これは、ほとんどのワイヤレス充電器に共通する現象です。また、高温環境ではパッテリーの劣化が進みやすいため、25℃未満の環境での充電を推奨いたします。

PD3.0 QC4.0+ PPS

S: 3.3-11V ... 2A(Max 22W)

製品素材:ABS+PC(WH) 製品素材:PC(BK)

5.対応急速充電規格

Due to its characteristics, wireless charging is slower than wired chargers.

If there is any liquid leakage from the product, stop using it immediately.

Follow the instructions of your local government when disposing of this product.

Do not use it in an environment where heat tends to accumulate (such as Number of cycles: Approx. 300 times

using CIO's battery withdraw service.

4.仕様

マグネットワイヤレス充雷:5W/7.5W/10W/15W

▲製品を廃棄する場合、各自治体の指示に従って廃棄してください。

製品本体から液漏れが発生した場合には、直ちに使用を中止してください。

Do not use this product near flammable oil, chemicals or flammable substances.

3.付属品

USB-C PD入力:5V=3A / 9V=2A / 12V=1.5A(Max 18W)

③電源ボタン(電源オフは 電源ボタンをダブルクリック) ④USB-C入出力ポート

・ルモビロ風いただき、デバイスへ投続します。 ②電源ボタンを3秒長押しし、残量表示LEDに緑の急速充電マークが点灯し 有線での急速充電が可能になります。

ラマ ⑤パッテリー残量LED



agSafe対応デバイスやQi2対応デバイスの場合、上図のように製品本体に

ぐワイヤレス充電中に本製品からデバイスを離し充電を止めた後に、ワイヤレス充電の 再開をする場合は電源ボタンを押すか、1度電源をオフにした後に再度電源オンにし で使用タイタ場合。

4. Apple Watchの充電 (スマートフォン以外の小型デバイス)の場合



Apple Watchが落下する恐れがあります。安定した場所でご使用ください ●Apple Watchへの出力は最大2.5Wとなります。

3. Wireless Charging for

in the image above.

and device is misaligned.

Small Devices Other than Smartphones

Wireless Charging Point Wireless Charging Area

or AirPods that support MagSafe charging, wireless charging will

start when the AirPods are adsorbed onto the product body as shown

When using wireless charging, please be careful of the position of the

*Operation with all wireless devices is not guaranteed.
*Charging time varies depending on device performance and battery level.

product as it may not charge properly if the position of the product

*The wireless charging point

●ワイヤレス充電を使用すると、本製品及びデバイスが熱くなることがあります が異常ではありません。デバイス側が満充電に近づくにつれ通常の温度に戻 バンドの種類により充電位置が不安定になることがあります。ご注意くだ。 ▶「パッテリー充電の最適化」を解除することで80%を超える充電が可能と 【バッテリー充電の最適化の解除方法】

※2台同時充電が正常に動作しないデバイスについては、1台ずつ充電して

4. Charging your Apple Watch

SMARTCOBY Ex02

6. パススルー充電

されます。



②MagSafe対応のスマートフォンなどを、上図のように製品本体の ワイヤレス充電エリアに吸着・設置すると、パススルー充電が開始

①製品本体と充電器を充電ケーブルにて接続します。

●パススルー充電は通常の充電よりも時間がかかります。

5. Two Device Simultaneous Charging

product as shown in the image above.

Wireless charging begins by adsorbing and placing a MagS compatible smartphone, etc., on the wireless charging area of t

Onnect this product and a device that supports cable chargin with a charging cable and charging will begin.

•Simultaneous charging of two devices may cause the produc become hot due to high power output, but this is not a malfunct

•When charging two devices at the same time, the green lightning mark

•If you charge two devices at the same time, the output to each devic will be lower, so charging will take longer.

Charging speed and time vary depending on the connected device

Wireless charging is up to 15W and cable charging is up to 20% total output of 15W

●本製品は「完全パススルー充電」機能を備えています。この機能により、 パイルパッテリーがフル充電された後、自動的に直流回路がスマートフ ンのワイヤレス充電に切り替わります。これにより、モバイルパッテリー 充電を停止し、スマートフォンの充電に集中すると担急となっています。 ●充電器は別売りです。別途ご準備ください。(18W以上の充電器を推奨) 5デバイスにより、充電速度・時間は異なります。

SMARTCOBY Ex02

付属のUSB-Cケーブルを使用して、充電アダプターに接 続します。本製品に接続後、USB-Cポートのある面のバッ

商品に初期不良などの不具合がある場合、レビューの前にご連絡ください。 初期不良品として交換対応を実施させていただきます。

納品書兼保証書もしくは、販売店レシートが

●最大18Wの急速蓄電をおこなうためには、18W出力に対応した電源アダブ

3. 火災・水害などによる故障。

メールアドレス customer@connectinternationalone.co.jp メリット02 LINE限定クーポン Amazonや楽天市場等でご利用いただける超お得なクーポンを INEでいち早く公開! SALEや新商品の情報も盛りだくさんです!

COUPON & SALE

CIOの製品の特長を分かりやすく解説!あなたに合うベストな製品が見つかる







Stay Updated with

All the Latest News!

We will be posting information abo

our new crowdfunding projec new products, and special discoun

The date of purchase:

Dealer's Name

Email address: smartcoby@connectinternationalone co in

One Year Warranty[CIO-MB20W1C-5000-EX02]

フォローしてね!

メリット 01 LINEでカスタマーサポート